

## **4K BYOM** wireless Pro





## > Connection diagram:



## Features

Linux
RK3566
A55 Quad-core 1.8GHz
2GB + 16GB
1*HDMl2.0, Max 4K60, can be set 11 resolutions
1*HDMI1.4, Max 1920*1080P60
1.35mm audio interface
1*LAN
2*USB-A2.0, 1*USB-C2.0
12V/2A
Max 9 split screens, can be set on WEB, default 9 split screens
64
Single screen: max 4K, 2-4 split screens: max 1080p, 5-9 split screens: max 720P
Proportions, 16:9, 16:10, 4:3
Support H264 & H265, max resolution 4K, max frame rate 60fps
44.1KHz 16bit stereo, HDMI embedded audio and 3.5mm audio
WiFi6 2T2R
WiFi5 2T2R
802.11ax, 802.11ac, 802.11n
50m
2.4G & 5G (Default 5G)
20 channel can be set, including 11 channels of 2.4G, and 9 channels of 5G
<150ms
Support MAC, iOS, WIN, Android and Harmong OS
USB-A / USB-C / HDMI transmitters
WIN Sender, Android Sender
Support Airplay, max resolution 4K
Support Miracast, max resolution 4K
HDMI input can loop out to HDMI output
Support USB and HDMI camera, USB microphone and USB speaker
Four screen mode in landscape orientation on mobilephone Four screen mode in portrait orientation on mobilephone
Built-in WEB setting
WIN controller
Android controller
<6W (not including the power of external devices like USB camera)
180mm*40mm*110.9mm (not include external glue stick antenna)
Running : $+5^{\circ}$ C ~ $+40^{\circ}$ C Storage : $-20^{\circ}$ C ~ $+60^{\circ}$ C
Running and Storage: 0 - 90°C , relative humidity, no condensation







Standard security

Support wired and wirless bridge

Support Airplay / Miracast

Support Max 9 split screens

Support touch-back

Support PIN Code

Support portrait display

Support BYOM application

Support automatic full screen display

Support extended mirroring

Support one RX to many TX

Support USB disk display

Support centralized management

Hardware update free







www.comreon.com